500W Digital Audio Video Amplifier – LUCKY TONE

Description:

With rigid structure and dynamic sound, LT-9000 5.1 Channel Hi-fi home theater amplifier is perfect for your home entertainment system, giving you super high power to be used for speakers and subwoofer to build a live experience.

Features:

1. With DTS Dolby Surround dual decoding function

2. 3 in 1 out HDMI HD interface, supports AC-3/DTS/PCM and other format decoding.

3. With the latest dual decoding chip, supporting (AC-3, DTS, PCM) fiber, coaxial, and HD decoding.

4. Built-in Mp3/TUNER/Bluetooth/USB/SD card module with screen display

5. High-speed central processing unit, automatically recognize audio input signals

6. Individual input gain controls with master volume control

7. With a full-function infrared remote controller

Model	**LT-9000**
Output	4-16ohm
Total Output Power	500W
Main Channel Output Power	100W*2
Center Channel Output Power	80W
Surround Channel Output Power	60W*2
Bass Channel Output Power	100W
SNR	≥75dB
THD	Less than 0.5% at 1kHz
Separation	≥45dB
Input Sensitivity	<500mv
Frequency response	
Front Channel	10Hz-40KHz(±2dB)
Surround Channel	10Hz-40KHz(±2dB)
Center Channel	10Hz-40KHz(±2dB)
Bass Channel	10Hz-200Hz(±2dB)
Treble Adjustment	Front channel ±14dB(10KHz)
Bass Adjustment	Front channel ±14dB(100Hz)
Gross Weight	9kg

Power Requirement	AC220V±10%, 50Hz±1Hz
Power Consumption	720W
Product Dimensions	440 x 360 x 90mm

